



High quality, professional 2-channel, 31-band graphic equalizer for accurate tuning of the frequency response, and feedback control. Highly effective for enhancing the audio experience of any sound installation. Ideal for a wide variety of PA and Pro Audio applications.

- Two independent 31 band graphic equalizers in 1/3 octave Constant Q frequency bands.
- Switchable cut/boost range of 6dB and 12dB. Low-cut filter ON/OFF switch for each channel.
- Equalizer bypass switch easily accessible on front panel.
- Input control has a gain range from -12dB to +12dB.
- Four segment LED indicator for monitoring output levels and a Clip LED for each channel.
- Electronically balanced inputs and outputs available through XLR connectors and 6.3mm (1/4") stereo phone jacks.
- 19" rack mountable in 2U size and usable as a table top unit also.

SPECIFICATIONS

INPUT IMPEDANCE	40k Ω Balanced/20k Ω Unbalanced
MAX INPUT LINE LEVEL	+21dBu
OUTPUT IMPEDANCE	200 Ω Balanced/100 Ω Unbalanced
MAX OUTPUT LEVEL	+20dBu
SIGNAL TO NOISE RATIO	100dB
FREQUENCY RESPONSE	20-20,000Hz (-1dB)
POWER REQUIREMENT	220-240V AC 50/60Hz
DIMENSION	W483 × H90 × D180 mm
WEIGHT	3.70kg

Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances. We cannot be held responsible for printing errors, should they occur. AHUJA is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2017. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of this compilation may be reproduced in any manner or translated without written permission.

AHUJA RADIOS

215, Okhla Industrial Estate, New Delhi-110020, INDIA
C-45, Phase-II, Noida-201305 (UP) INDIA ● 3, Okhla Industrial Estate, New Delhi-110020 INDIA
Tel.: +91-11-26831549, 41612474 Fax: +91-11-26847287 E-mail: ahuja@ahujaradios.com
Website: www.ahujaradios.com

001108