

### Dual Channel Receiver 2 x Handheld Transmitter



Ahuja introduces elegant & reliable dual channel Wireless Microphone **AWM-520V2**. It features two dynamic handheld transmitters and a sensitive two channel VHF receiver. Special ALC circuit provided to handle high sound pressure levels.

- Elegant and affordable dual channel VHF wireless microphone available in different frequencies.
- Dynamic unidirectional handheld transmitter with a three position slide switch and Low Battery LED indicator.
- Stylish table-top receiver with noise squelch circuitry.
- ALC circuit handles high sound pressure levels without distortion.
- Separate output volume controls for both channels on the front panel of the receiver.
- Power ON/OFF switch and 6.3mm phone jack for audio output on the rear panel of the receiver.
- Each transmitter operates on 1×9V battery.
- Receiver operates on 12V DC through an AC adaptor, supplied along with the microphone.

#### TRANSMITTER

RF Output Power	10mW (Max.)
Modulation Mode	FM
Capsule	Dynamic, Cardioid
Maximum Deviation	±25kHz
Frequency Response	40Hz-15kHz
Power Requirement	9V Battery
Current Consumption	<30mA
Controls	ON/MUTE/OFF Switch
Dimensions	ø 48 (L 240) mm
Weight	0.25kg (without battery)

#### RECEIVER

Frequency Stability	± 0.005%
Audio Output (Nominal)	0-50mV adjustable
S/N Ratio	>90dB
Distortion	<0.5%
Antenna Type	Telescopic
Power Requirement	220V-240V AC 50Hz for AC adaptor (supplied alongwith)
Controls	Power Switch, Output Volume Controls for channel A & B
Dimensions	W200 × H55 × D155 mm
Weight	0.35kg

**ACCESSORIES** 1×Connection Cable, 1×AC Adaptor, 2×9V Battery

Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances. We cannot be held responsible for printing errors, should they occur. **AHUJA** is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2013. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of this compilation may be reproduced in any manner or translated without written permission.

#### AHUJA RADIOS

215, Okhla Industrial Estate, New Delhi-110020, INDIA  
C-45, Phase-II, Noida-201305 (UP) INDIA ● 3, Okhla Industrial Estate, New Delhi-110020 INDIA  
Tel.: +91-11-26831549, 41612474 Fax: +91-11-26847287 E-mail: [ahuja@ahujaradios.com](mailto:ahuja@ahujaradios.com)  
Website: [www.ahujaradios.com](http://www.ahujaradios.com)