



12", 200W Dual Cone Speaker 2" CCAW High Temperature Voice Coil



Dimensions



Frequency Response Curve



200
Watts
RMS

Features

- 12" dual cone speaker with a continuous power handling capacity of 200 watts RMS.
- Pressed steel frame and robust construction.
- Well balanced, wide spectrum frequency response.
- High quality specially designed imported cones and spider for extremely clear, low distortion sound reproduction.
- Imported 2" CCAW voice coil with high temperature rating for safe, reliable operation.
- Ideal for keyboard, musical & wide variety of PA applications.

Specifications

POWER RATING	200W RMS
NOMINAL DIAMETER	305 mm (12")
NOMINAL IMPEDANCE	8Ω
SENSITIVITY (1W/1m)	97dB
MAGNET WEIGHT	1.16kg
RESONANT FREQUENCY (Fs)	50Hz
DC RESISTANCE (Re)	6.8Ω
ELECTROMAGNETIC Q (Qes)	0.92
MECHANICAL Q (Qms)	3.26
TOTAL Q (Qts)	0.72
SURFACE AREA OF CONE (Sd)	510cm ²
REFERENCE EFFICIENCY (ηo)	3.6%
VOICE COIL DIAMETER	2.0"
OVERHANG (Xmax)	2.5 mm
MOVING MASS (Mms)	36.7gm
BL PRODUCT (BL)	11.2TM
COIL INDUCTANCE (Le)	0.69mH
OVERALL DIAMETER	313 mm
DEPTH	127 mm
BAFFLE HOLE DIAMETER	285 mm
BOLT MOUNT DIAMETER (PCD)	295 mm (8 Bolts)
WEIGHT	4.16kg approx.

Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances.

We cannot be held responsible for printing errors, should they occur. AHUJA is a registered trademark of Ahuja Radios in India and other countries.

© Copyright Ahuja Radios, 2014. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law.

No part of this compilation may be reproduced in any manner or translated without written permission.

AHUJA RADIOS

215, Okhla Industrial Estate, New Delhi-110020, INDIA
C-45, Phase-II, Noida-201305 (UP) INDIA
Tel.: +91-11-26831549, 41612474 Fax: +91-11-26847287
E-mail: ahuja@ahujaradios.com Website: www.ahujaradios.com